

AMPLIFIER

The music **vibrates** in the memory



KA-120 II

DIGITAL ECHO KARAOKE AV AMPLIFIER

- 16 Bits Digital Echo(16位元數位迴音)
- 9 Steps Key Shift(9段移調)
- Remote Control(全功能遙控)
- Speaker Protection(喇叭保護裝置)
- Input Level Adjustment(輸入準位調整)
- Auto Volume Setting(Initial)
(開機時·音量及麥克風旋鈕自動設定裝置)
- 4 Sources Input Select(Auto/Manual)
(具4組輸入音源[自動/手動]選擇)
- Output輸出功率150W+150W



 **ANTZEER**

AMPLIFIER



KA-120 II

KA-120II SPECIFICATION

1. Amplifier Maximum Output 150W+150W/8Ω(EIAJ)
2. Total Harmonic Distortion 0.03%
3. Audio Input/output Impedance
 - MIC 6mV/600Ω
 - CD, DVD, AUX, BGM 300mV/22KΩ
 - PRE-output 2.5V/1KΩ
 - REC-output 600mV/1KΩ
4. Frequency Responses
 - MIC 10Hz~25kHz/±3dB
 - MUSIC 10Hz~40kHz/±3dB
5. Tone Control Characteristics
 - Microphone BASS ±10dB(100Hz)
 - TREBLE ±10dB(10kHz)
 - Music BASS ±10dB(100Hz)
 - TREBLE ±10dB(10kHz)
6. Speaker Output Terminals
 - (1)system only, 1 or 2 4~16Ω
 - (2)system, 1 and 2 6~16Ω
7. Key Control Range ±2Tones(9 steps)
8. Video Input/output Impedance 1Vp-p/75Ω
9. Power Supply, etc.
 - supply voltage 110~120V/220~240VAC, 50~60Hz
 - Power Consumption 325W
10. AC Power Outlets
 - SWITCHED(200W max) 1
 - UNSWITCHED(300W max) 1
11. Dimentions(W*H*D) 420*130*398mm
12. Weight 14kg

 **ANTZEER**

