

# P Series Controller



注意：配PS10TD为PS10和LS500系统组合的声音处理专配设计，设有反馈保护系统对与单元保护及系统总体声音品质具有很好的保证。

Mode	PS10TD
Audio Inputs	Two L&R Audio inputs. Electronically balanced, 36 kOhm. Two XLR-3F connectors.
Sense Inputs	Three Amplifier Sense Inputs (PS10 L&R, Ls500). 150 kOhm. 6 Pole Removable Strip Terminal.
Audio Outputs	Two L&R PS10 Audio outputs. Electronically balanced, 50 Ohm. Two XLR-3M.
Controls	Std/Max Protection Trimmer. Gain switch (back panel), 3 positions for Amps with Gain : 26 / 32 / 38 dB. Sub On switch & Sub Gain Control.
Indicators	Speaker Protect LED' s. Amp Sense & Peak LED' s.
Output Level	+20 dBm Max. +19dBm Max on 1kOhm
Noise	-88 dBm (22 Hz - 22 kHz, UnWeighted)
THD+N	< 0.03% Typ. 0.05 Max for +18dBm Output
Power Supply	110/220 Volts (internal wiring), 50/60Hz.
Applicable Products	The PS10 TDController is precisely matched to the PS10 & LS500 cabinets and includes sophisticated protection systems. Use of either product without a properly connected Controller will result in poor sound quality and may damage the components.
Subbass	Active two-way operation of the PS10 Loudspeaker with the LS500 Subwoofer is included in the PS10TD.
Packing Dimensios(HxWxD)	482MMx44MMx170MM
Gross Weight	2.9kg