



GIGRAC 600
Integrated mixer and 2x300W amplifier



GIGRAC 1000st

- Available in 2 models : Gigrac 600 & Gigrac 1000st
- 8 channel mixer
- XLR , jack and phono inputs
- 2-band channel equalisation (Gigrac 600)
- 3-band channel equalisation (Gigrac 1000st)
- On-board 7-band graphic equalisation
- High quality digital effects porgrammes
- 10-segment precision LED metering
- Independent Main and Monitor mixes



GENERAL SPECIFICATIONS

Model	GIGRAC 600	GIGRAC 1000ST
Frequency Response	20Hz-22kHz rel 1kHz Line in to Main out+0.2/-2.5dB	
T.H.D.	Mic I/P-20dB pad 0dBu I/P at Main out (22Hz-22kHz).....0.15% Mic I/P to Amp Out @full power (22Hz-22kHz).....0.15%	
Power Amp@4 Ohms	2 x 300W	2 x 500W
Frame Sizes	8	8
Stereo Channels	4	4
FX Processors	1	1
EQ Bands	2 band fixed	3 band fixed
Aux Sends	1	1
Returns	2	2
Phantom Voltage	48V	48V
Size (Uncased) Hx Wx D	4U 222mmX495mmX322mm	5U 267mmX495mmX322mm
Weight	12.7Kg	13Kg